

# How to hide translated number for the Speed Dial feature

## Description:

How to hide translated number for the Speed Dial feature

When a call is translated from our server, the phone shows the translated number. This guide helps you to hide the full number.

## How-to:

1. Create new Partition and CSS in CUCM configuration  
 Example:  
 PT-SpeedDial  
 CSS-SpeedDial
2. Add the new Partition in the CSS used by the phone
3. Create a Translation Pattern and configure it with the new Partition and CSS, set the ECC Profile to invoke our server for the SpeedDial requests

**Status**  
 Status: Ready

**Pattern Definition**

Translation Pattern: 88XX

Partition: PT-SpeedDial

Description: SpeedDial

Numbering Plan: < None >

Route Filter: < None >

MLPP Precedence\*: Default

Resource Priority Namespace Network Domain: < None >

Route Class\*: Default

Calling Search Space: CSS-SpeedDial

Use Originator's Calling Search Space

External Call Control Profile: ECC204.214

Route Option:  
 Route this pattern  
 Block this pattern No Error

Provide Outside Dial Tone

Urgent Priority

Do Not Wait For Interdigit Timeout On Subsequent Hops

Route Next Hop By Calling Party Number

**Calling Party Transformations**

Use Calling Party's External Phone Number Mask

Calling Party Transform Mask:

Prefix Digits (Outgoing Calls):

Calling Line ID Presentation\*: Default

Calling Name Presentation\*: Default

Calling Party Number Type\*: Cisco CallManager

Calling Party Numbering Plan\*: Cisco CallManager

4. Create a new Route Pattern as the Route Pattern used for the outgoing calls and configure it in the new Partition , then change the Connected Line ID Presentation/Connected Name Presentation in "Restricted"

System > Call Routing > Media Resources > Advanced Features > Device > Application > User Management > Bulk Administration > Help

**Find and List Route Patterns**

Add New Select All Clear All Delete Selected

Status 10 records found

**Route Patterns (1 - 10 of 10)** Rows per Page 50

Find Route Patterns where Pattern begins with 0 Find Clear Filter

Pattern	Description	Partition	Route Filter	Associated Device	Copy
01	AG-Uspota VG Milano	PT-PSTN_AG	VG6		
01	PSTN through SBC AudioCodes	MICROSOFT-TEAMS-AUDIOCODES	SBCMSippSoftTeams		
01	PSTN through Milano VG	PT-MI-CHIAMATELOCALI	VG6		
01	PSTN through Milano VG	PT-SBESBC6E	VG6		
01	PSTN through Milano VG	PT-VG-PSTN	VG6		
00	Outgoing Ext calls through (ahmedtest)	PT-DU-PHONES	CLICH_Erad		
00035	Outgoing External calls through Viareggio VG	PT-DU-SHTL	192-168-4-4		
020921864414920		PT-MI-INTERNATIONAL	VG6 - NEW		
02403746458		PT-MI-CHIAMATELOCALI	VG6		
024X	Recording Bug Test Michele	PT-MI-CHIAMATELOCALI	CallRecorder-Michele		

Add New Select All Clear All Delete Selected

**Route Pattern Configuration**

Save ✖ Delete 📄 Copy ➕ Add New

---

**Status**  
📘 Status: Ready

---

**Pattern Definition**

Route Pattern*	<input type="text" value="0.1"/>	
Route Partition	<input type="text" value="PT-SpeedDial"/>	
Description	<input type="text" value="PSTN through Milano VG"/>	
Numbering Plan	<input type="text" value="-- Not Selected --"/>	
Route Filter	<input type="text" value="&lt; None &gt;"/>	
MLPP Precedence*	<input type="text" value="Default"/>	
<input type="checkbox"/> Apply Call Blocking Percentage	<input type="text"/>	
Resource Priority Namespace Network Domain	<input type="text" value="&lt; None &gt;"/>	
Route Class*	<input type="text" value="Default"/>	
Gateway/Route List*	<input type="text" value="VGs"/>	<a href="#">(Edit)</a>
Route Option	<input checked="" type="radio"/> Route this pattern <input type="radio"/> Block this pattern <input type="text" value="No Error"/>	
Call Classification*	<input type="text" value="OnNet"/>	
External Call Control Profile	<input type="text" value="&lt; None &gt;"/>	
<input type="checkbox"/> Allow Device Override <input type="checkbox"/> Provide Outside Dial Tone <input type="checkbox"/> Allow Overlap Sending <input type="checkbox"/> Urgent Priority		
<input type="checkbox"/> Require Forced Authorization Code		
Authorization Level*	<input type="text" value="0"/>	
<input type="checkbox"/> Require Client Matter Code		

---

**Calling Party Transformations**

<input type="checkbox"/> Use Calling Party's External Phone Number Mask	
Calling Party Transform Mask	<input type="text"/>
Prefix Digits (Outgoing Calls)	<input type="text"/>
Calling Line ID Presentation*	<input type="text" value="Default"/>
Calling Name Presentation*	<input type="text" value="Default"/>
Calling Party Number Type*	<input type="text" value="Cisco CallManager"/>
Calling Party Numbering Plan*	<input type="text" value="Cisco CallManager"/>

---

**Connected Party Transformations**

Connected Line ID Presentation*	<input type="text" value="Restricted"/>
Connected Name Presentation*	<input type="text" value="Restricted"/>