imagicle[.]

Skype for Business Configuration Wizard

In case deployment has been done with UC Suite installation package, when installation ends, User is automatically asked to run Call Analytics' configuration wizard.

In case deployment has been done with UC Suite Virtual Appliance, Call Analytics' configuration wizard needs to be manually launched by user.

Access to Imagicle UC Suite server with RDP session and hit Windows "Start" menu.

Search for "Imagicle Call Analytics Configuration" and launch the tool as Administrator.



Call Analytics configuration wizard guides the user through the configuration steps described below.

imagicle⁻

Blue's Configuration	- PBX Connection
Connection type Specify here how the computer is connected to the	PBX.
Insert a reference name for this PBX:	<mark>S48</mark>
Indicate the connection type with the PBX:	
I'm connected to the Pbx via TCP/IP	Microsoft Skype For Busine 💌
	< Back Next > Cancel

In the next window it is possible to enter the Gateway Connection details.

≞L Blue's Co	onfiguration	- PBX connection	x
Communication settings Specify here the configuration settir	ngs to access the	PBX.	
SFB Monitoring SQL Server: Database: Security:	Sfb.imagidetv LcsCDR Use Window Use SQL Se Domain: User: Password:	xs domain user: erver user and password: imagicletv.com Administrator *********	
		< Back Next > Ca	ancel

Imagicle Call Analytics configuration process displays a window with a full summary of the list of the configured S4B Front Ends, click Next to proceed

imagicle[.]

<u>≞</u> L	Blue's Configuration - PBX Connection				
Configu You can Press Fir	edit a PBX allready co nish to complete the c	nfigured or add a new one. onfiguration.			
	List of configured I	PBXs			
	PBX	Connection	Registration		
	S48	TCP/IP Network	Registered		
		New PBX Edit	Delete		

In the next S4B specific window, you can select the driver to be used.

*	Billy Blue's	setup wizaro	I - PABX:	S4B		x
Driver Select the driver provided by the	that Blue's Miner sho PBX.	uld use to corre	ctly interpret	t the call tick	ets	
O Use the dr	iver found by the au	utomatic search				
Driver fou	nd:				Details	
	Find dr	iver automatical	ly			
Select the	driver manually					
DBV brand		Nodel				
P by brand	<u></u>	modet.				
Microsof	2	Skype F	or Business v	/1 .9 3		
			< Back	Next >	Cancel	
						_

Click on next to check parameters have been properly configured.

imagicle[.]

*	Billy Blue's setup wizard - PABX: S4B
Driver pa The sele Please t	arameters ected driver requires further information to correctly decode the call ticket. type the requested data.
0	Parameters correctly configured.
	< Back Next > Cancel

Click on edit to perform additional numbering plan configuration, if required.

Configuration	×
Use Sip URI as Extension (1=yes and recommended, 0=no)	
Insert here a list of prefixes to remove from remote number in outgoing calls	
	^
	~
Insert here a list of prefixes to remove from remote number in incoming calls	
	^
	~
OK Cancel	

Click on OK an then on next to select the type of management for internal calls.

imagicle⁻

*	Billy Blue's setup wizard - PABX: S4B
Internal calls Select the type	of management for internal calls.
O Do not impo	rt internal calls
Import inter	nal calls
	< Back Next > Cancel

Then click next to enter the Tariffs and Tariff Comparison, explained in the <u>next KB page</u>